

Gen Set Power Selector Chart

Model offering for Unregulated Territories

2010 Issue 2

50Hz

Model	Net Engine Output			Typical Generator Efficiency %	Typical Power Factor	Typical Generating Set Output						1500/1800 rev/min switchable
	Baseload kWm	Prime kWm	Standby kWm			Baseload		Prime		Standby		
				kWe		kVA	kWe	kVA	kWe	kVA		

3000 rev/min (8.3 kVA to 36.4 kVA)

402D-05G [✦]	*	7.7	8.5	86	0.8	*	*	6.6	8.3	7.3	9.1	
403D-07G [✦]	*	11.5	12.6	86	0.8	*	*	9.9	12.3	10.8	13.5	
403D-11G	*	16.5	18.1	86	0.8	*	*	14.2	17.7	15.6	19.5	
403D-15G	*	20.2	22.2	87	0.8	*	*	17.6	21.9	19.3	24.1	
404D-22G	*	29.7	32.7	89	0.8	*	*	26.5	33.1	29.1	36.4	

1500 rev/min (9 kVA to 2500 kVA)

403D-11G	*	8.4	9.2	86	0.8	*	*	7.2	9.0	7.9	9.9	
403D-15G	*	12.0	13.2	87	0.8	*	*	10.4	13.0	11.4	14.3	
404D-22G	*	18.4	20.3	88	0.8	*	*	16.2	20.3	17.8	22.3	
404D-22TG	*	24.3	26.7	90	0.8	*	*	21.8	27.3	24.0	30.0	■
1103A-33G	*	27.7	30.4	87	0.8	*	*	24.0	30.0	26.4	33.0	■
1103A-33TG1	*	41.3	45.6	87	0.8	*	*	36.0	45.0	39.7	49.6	■
1103A-33TG2	*	53.8	59.3	89	0.8	*	*	48.0	60.0	52.8	66.0	■
1104A-44TG1	*	58.4	64.3	89	0.8	*	*	52.0	65.0	57.2	71.5	■
1104A-44TG2	*	71.9	79.1	89	0.8	*	*	64.0	80.0	70.4	88.0	■
1104C-44TAG2 (Stage 2 compliant)	*	90.1	99.5	90	0.8	*	*	81.4	101.4	89.6	111.9	■
1006TG1A	*	83.0	91.5	90	0.8	*	*	74.5	93.0	82.5	103.0	
1006TG2A	*	91.0	100.0	90	0.8	*	*	82.0	102.5	90.0	112.5	
1006TAG	*	121.0	133.5	90	0.8	*	*	109.0	136.0	120.0	150.0	■
1006TAG2	*	129.3	143.0	93	0.8	*	*	120.0	150.0	132.0	165.0	
1106C-E66TAG4	*	158.4	175.5	93	0.8	*	*	147.3	184.1	163.2	204.0	■
1306C-E87TAG3	164	180	199	92	0.8	151	189	166	208	183	229	■
1306C-E87TAG4	179	198	217	92	0.8	165	205	182	228	200	250	■
1306C-E87TAG5	185	204	224	92	0.8	170	213	188	235	206	258	
1306C-E87TAG6	198	217	239	92	0.8	182	228	200	250	220	275	
2206A-E13TAG2	*	305	349	92	0.8	*	*	280	350	320	400	■
2206A-E13TAG3	*	349	392	92	0.8	*	*	320	400	360	450	
2506A-E15TAG1	*	396	434	92	0.8	*	*	364	455	400	500	■
2506A-E15TAG2	*	435	478	92	0.8	*	*	400	500	440	550	■
2806A-E18TAG1A	*	522	574	92	0.8	*	*	480	600	528	660	■
2806A-E18TAG2	*	565	609	92	0.8	*	*	520	650	560	700	■
4006-23TAG2A	505	632	695	95	0.8	480	600	600	750	660	825	
4006-23TAG3A	540	679	760	94	0.8	512	640	640	800	720	900	
4008TWG2	560	710	782	95	0.8	532	665	675	843	743	929	
4008TAG	566	715	787	95	0.6	538	672	679	849	748	935	
4008TAG1A	606	767	844	95	0.8	576	720	728	911	802	1002	
4008TAG2A	681	861	947	95	0.8	647	809	818	1022	900	1125	
4012-46TAG0A	842	1053	1158	95	0.8	800	1000	1000	1250	1100	1375	
4012-46TWG2A	833	1055	1166	95	0.8	791	989	1002	1253	1108	1385	
4012-46TWG3A	909	1149	1263	95	0.8	864	1079	1092	1364	1200	1500	
4012-46TAG1A	909	1148	1263	95	0.8	864	1080	1091	1364	1200	1500	
4012-46TWG4A	-	1254	1342	96	0.8	-	-	1200	1500	1280	1600	
4012-46TAG2A	1005	1267	1395	95	0.8	955	1194	1204	1505	1325	1656	
4012-46TAG3A	1200	1440	1583	95	0.8	1140	1425	1368	1710	1504	1880	
4016-61TRG1 [✦]	1178	1558	1684	96	0.8	1120	1400	1480	1850	1600	2000	
4016TAG1A	1219	1537	1690	96	0.8	1170	1463	1476	1844	1622	2028	
4016-61TRG2 [✦]	1347	1684	1894	96	0.8	1280	1600	1600	2000	1800	2250	
4016TAG2A	1362	1715	1886	96	0.8	1307	1634	1646	2058	1811	2263	
4016-61TRG3 [✦]	1500	1875	2083	96	0.8	1440	1800	1800	2250	2000	2500	

Gas Power 1500 rev/min (307 kWe to 1000 kWe)

4006-23TRS1 [†]	322	-	-	95.4	1	307	307	-	-	-	-	
4006-23TRS2 [†]	393	-	-	95.4	1	375	375	-	-	-	-	
4008-30TRS1 [†]	447	-	-	95	1	425	425	-	-	-	-	
4008-30TRS2 [†]	526	-	-	95	1	500	500	-	-	-	-	
4012TESI [†]	632	-	-	95	1	600	600	-	-	-	-	
4016-61TRS1 [†]	912	-	-	96	1	875	-	-	-	-	-	
4016-61TRS2 [†]	1042	-	-	96	1	1000	-	-	-	-	-	

*Available on application † Gross power

■ Switchable engines must be requested at point of order, please consult with your local Perkins representative.

✦ Available as Electro Unit only

Notes:

- All ratings are for guidance only, please refer to the specific engine technical data sheet for final powers.
- Perkins conditions of sale apply.
- Electrical output is based on typical generator efficiency and is for guidance only.
- All ratings data based on operation under ISO 8528-1, ISO 3046, DIN6271 conditions using typical fan sizes and drive ratios. Performance tolerance quoted by Perkins is ± 5%.
- **Baseload Power** = Power available for continuous full load operation. An overload of 10% permitted for one hour in every twelve hours of operation.
Please Note: No overload is permitted on 4000 Series.
- **Prime Power** = Power available at variable load in lieu of main power network (please refer to the engine Technical Data Sheets for engine load factors). An overload of 10% permitted for one hour in every twelve hours of operation.
- **Standby Power** = Power available at a variable load in the event of a main power network failure up to a maximum of 500 hours per year. No overload is permitted.

Gen Set Power Selector Chart

Model offering for Unregulated Territories

2010 Issue 2

60Hz

Model	Net Engine Output			Typical Generator Efficiency	Typical Power Factor	Typical Generating Set Output						1500/1800 rev/min switchable
	Baseload kWm	Prime kWm	Standby kWm			%	Baseload		Prime		Standby	
				kWe			kVA	kWe	kVA	kWe	kVA	

1800 rev/min (3.9 kWe to 1504 kWe)

402D-05G*	*	4.5	5.0	86	0.8	*	*	3.9	4.9	4.3	5.3	
403D-07G*	*	6.6	7.3	86	0.8	*	*	5.7	7.1	6.3	7.8	
403D-11G	*	10.4	11.4	87	0.8	*	*	9.0	11.3	9.9	12.4	
403D-15G	*	14.4	15.8	88	0.8	*	*	12.6	15.8	13.9	17.4	■
404D-22G	*	21.7	23.9	89	0.8	*	*	19.3	24.2	21.3	26.6	■
404D-22TG	*	28.8	31.7	89	0.8	*	*	25.6	32.1	28.2	35.3	■
404D-22TAG	*	31.5	34.7	90	0.8	*	*	28.4	35.5	31.2	39.0	
1103A-33G	*	32.2	35.4	87	0.8	*	*	27.9	34.9	30.6	38.2	■
1103A-33TG1	*	48.8	53.9	87	0.8	*	*	42.5	53.1	46.9	58.7	■
1103A-33TG2	*	61.2	66.4	89	0.8	*	*	54.5	68.1	60.1	75.1	■
1104A-44TG1	*	68.6	75.5	89	0.8	*	*	60.8	76.0	66.9	83.6	■
1104A-44TG2	*	82.0	90.2	89	0.8	*	*	73.0	91.3	80.3	100.3	■
1006TG1A	*	96.5	106.5	90	0.8	*	*	87.0	109.0	96.0	120.0	
1006TG2A	*	107.0	118.0	90	0.8	*	*	96.5	120.5	106.0	132.5	
1006TAG	*	134.0	147.0	90	0.8	*	*	120.5	151.0	132.5	165.5	■
1106C-E66TAG2	*	138.4	155.3	92	0.8	*	*	127.3	159.2	142.9	178.6	■
1106C-E66TAG3	*	146.4	163.4	92	0.8	*	*	136.1	170.1	152.0	190.0	■
1106C-E66TAG4	*	177.3	196.3	92	0.8	*	*	164.9	206.1	182.6	228.2	■
1106D-E66TAG2	*	136.6	153.6	92	0.8	*	*	125.0	156.0	140.0	175.0	
1106D-E66TAG3	*	142.4	159.4	92	0.8	*	*	135.0	169.0	150.0	188.0	
1106D-E66TAG4	*	173.7	192.3	92	0.8	*	*	160.0	200.0	175.0	219.0	
1306C-E87TAG3	182	201	220	92	0.8	167	209	185	231	202	253	■
1306C-E87TAG4	194	213	235	92	0.8	178	223	196	245	216	270	■
2206A-E13TAG5	*	349	381	92	0.8	*	*	320	400	350	438	■
2206A-E13TAG6	*	381	435	92	0.8	*	*	350	438	400	500	■
2506A-E15TAG3	*	446	490	92	0.8	*	*	410	513	450	563	■
2506A-E15TAG4	*	495	543	92	0.8	*	*	455	569	500	624	■
2506C-E15TAG4#	-	-	597	92	0.8	-	-	-	-	550	687	
2806A-E18TAG1A	*	543	598	92	0.8	*	*	500	625	550	687	■
2806A-E18TAG3	*	592	652	92	0.8	*	*	545	681	600	750	■
4006-23TAG2A	511	638	702	94	0.8	480	600	600	750	660	825	
4008TWG2	534	684	756	95	0.8	507	634	650	812	718	898	
4008TAG	564	712	784	95	0.8	536	670	676	846	745	931	
4006-23TAG3A	570	715	795	95	0.8	540	675	675	844	750	938	
4008TAG1	584	744	821	95	0.8	555	694	707	884	780	975	
4008TAG2	659	838	924	95	0.8	626	783	796	995	878	1097	
4012-46TWG2A	833	1055	1166	95	0.8	791	989	1002	1253	1108	1385	
4012-46TWG3A	909	1149	1263	95	0.8	864	1079	1092	1364	1200	1500	
4012-46TAG1A	914	1153	1267	95	0.8	868	1085	1095	1369	1204	1505	
4012-46TWG4A	-	1254	1342	96	0.8	-	-	1200	1500	1280	1600	
4012-46TAG2A	1009	1272	1399	95	0.8	959	1199	1208	1510	1329	1669	
4012-46TAG3A	1200	1440	1583	95	0.8	1140	1425	1368	1710	1504	1880	

1200 rev/min (592 kWe to 1478 kWe)

4008TAG1	491	623	686	95	0.8	466	583	592	740	652	815	
4008TAG2	547	693	763	95	0.8	520	650	658	823	725	906	
4016TAG	908	1146	1263	96	0.8	872	1091	1100	1375	1212	1515	
4016TAG2	1108	1400	1540	96	0.8	1063	1329	1344	1680	1478	1848	

Gas Power 1200 rev/min (576 kWe)

4012TESI†	600	-	-	96	1	576	576	-	-	-	-	
-----------	-----	---	---	----	---	-----	-----	---	---	---	---	--

*Available on application † Gross power # Emergency Standby Power only

■ Switchable engines must be requested at point of order, please consult with your local Perkins representative

❖ Available as Electro Unit only

Notes:

- All ratings are for guidance only, please refer to the specific engine technical data sheet for final powers.
- Perkins conditions of sale apply.
- Electrical output is based on typical generator efficiency and is for guidance only.
- All ratings data based on operation under ISO 8528-1, ISO 3046, DIN6271 conditions using typical fan sizes and drive ratios. Performance tolerance quoted by Perkins is ± 5%.
- **Baseload Power** = Power available for continuous full load operation. An overload of 10% permitted for one hour in every twelve hours of operation.
- **Please Note: No overload is permitted on 4000 Series.**
- **Prime Power** = Power available at variable load in lieu of main power network (please refer to the engine Technical Data Sheet for engine load factors). An overload of 10% permitted for one hour in every twelve hours of operation.
- **Standby Power** = Power available at a variable load in the event of a main power network failure up to a maximum of 500 hours per year. No overload is permitted.
- **Emergency Standby Power** = Power available in the event of a main power network failure, up to maximum of 200 hours per year which may be run continuously. Load factor may be up to 70% of the Emergency Standby Power rating. No overload is permitted.



Perkins Engines Company Limited
 Peterborough PE1 5NA United Kingdom
 Tel: +44 (0)1733 583000
 Fax: +44 (0)1733 582240
 www.perkins.com